





近接開關傳感器 耐彎抗拉圓管型系列 快選表

真誠 品質 速度 服務

品號	圖示	尺寸	安裝孔徑 規格	規格描述	電壓/電流	認證
PSC0801-NP		14.8x66mm	M8	Sensing distance: 1 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 8 mA no-load	CE
PSC0802-NP		14.8x66mm	M8	Sensing distance: 2 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 8 mA no-load	CE
PSD1202-NP		17x40mm	M12	Sensing distance: 2 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 14 mA no-load	CE
PSD1205-NP		17x40mm	M12	Sensing distance: 5 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 14 mA no-load	CE





近接開關傳感器 耐彎抗拉圓管型系列 快選表

真誠

品質

速度

服務

品號	圖示	尺寸	安裝孔徑 規格	規格描述	電壓/電流	認證
PSC1202-NP		17x80.5mm	M12	Sensing distance: 2 mm \pm 10% Switching frequency: 800 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 14 mA no-load	CE
PSC1205-NP		17x80.5mm	M12	Sensing distance: 5 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 14 mA no-load	CE
PSD1805-NP		24x36.4mm	M18	Sensing distance: 5 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 14 mA no-load	CE
PSD1808-NP		24x36.4mm	M18	Sensing distance: 8 mm \pm 10% Switching frequency: 500 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: \leq 14 mA no-load	CE





近接開關傳感器 耐彎抗拉圓管型系列 快選表

真誠

品質

速度

服務

品號	圖示	尺寸	安裝孔徑 規格	規格描述	電壓/電流	認證
PSC1805-NP		24x75.5mm	M18	Sensing distance: 5 mm $\pm 10\%$ Switching frequency: 600 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: ≤ 14 mA no-load	CE
PSC1808-NP		24x75.5mm	M18	Sensing distance: 8 mm $\pm 10\%$ Switching frequency: 600 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: ≤ 14 mA no-load	CE
PSC3010-NP		36x80.3mm	M30	Sensing distance: 12 mm $\pm 10\%$ Switching frequency: 300 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: ≤ 16 mA no-load	CE
PSC3018-NP		36x80.3mm	M30	Sensing distance: 18 mm $\pm 10\%$ Switching frequency: 300 Hz	Working Voltage: DC12 ~ 30 V Consumption Current: ≤ 16 mA no-load	CE